

LTX-552X Digital Fiber Optic Link

Features:

- Channel capacity up to 50 Mb/S
- Outputs are LVTTTL (0 - 3.3 V)
- Accepts LVTTTL and/or CMOS/TTL inputs
- 1310 nm version for SM links up to 10 KM
- 850 nm version for multimode links up to 500 Meters
- Transmits 16 independent TTL signals over a single fiber
- Paired with LTX-551x to configure remote high speed 12 or 14-bit A/D and D/A converter modules



Digital Fiber Optic Link

The LTX-552x conveys sixteen independent channels of digital information over a fiber optic link ranging from meters to more than 10 kilometers.

Each of the 16 incoming TTL channels is sampled at up to 5×10^7 times per second, multiplexed and transmitted serially over an optical fiber at up to 2 gigabit per second. The receiver acquires this digital data and de-multiplexes it to 16 separate output ports. Each of these channels may be toggled at rates ranging from 0 to 48 Mb/S.

Two models are available. The LTX5520 transmits serially at 1 gigabit and the LTX5525 transmits at 2 gigabit over either SM or MM fibers. The distance between units determines the fiber required to complete the link. 850 nm units operate on multi-mode fiber up to 500 meters in length, while 1310 nm units operate with single-mode fiber to span distances exceeding 10 kilometers.

The LTX-5510 precision analog fiber optic link was the first in our series of "Signal Transporters". It digitizes an analog signal at a 50 Ms/S rate with 12-bit precision and reconstructs the signal at the LTX-5510 receiver by means of a fast D/A converter. If the user employs the LTX-5520 receiver with the LTX-5510 transmitter, the result is a remote fiber-coupled 12-bit data acquisition system.

Similarly one can employ the LTX-5520 transmitter with the LTX-5510 receiver to generate fast high-resolution analog signals at a remote location.

Applications include data acquisition for plasma physics experiments, signal transmission and control of equipment at high voltage potentials, operation through Faraday shields, and precise noise-free signal transmission in hostile EMI environments.



Made In the USA

Terahertz Technologies Inc.

169 Clear Rd., Oriskany NY 13424

Toll Free: 855-TTI-TEAM

Phone: 315-736-3642 Fax: 315-736-4078

E-mail: sales@teratec.us

Web: www.teratec.us

LTX-552X-Specifications

	LTX-5520	LTX-5525
Number of independent Channels	16	
Signal Latency (with one meter of fiber)	Approximately 300 ns	
Input Impedance	50 Ohms or 1 Megohm 20 pF, selectable	
Output Drive Capability	+/- 5 V open circuit, +/- 2 V into 50 ohm load	
Output Impedance	50 Ohms	
Digital Inputs	TTL, LVTTTL, CMOS compatible	
Digital Outputs	LVTTTL (0 - 3.3 V)	
Digital switching Rates	0-12.5 MHz (up to 24 Mb/s)	0-24 MHz (up to 48 Mb/s)
Digital Signal Edge Uncertainty	0 - 20 ns	0 - 10 ns
Laser Wavelength	850 nm +/- 20 nm or 1310 nm +/- 20 nm	
Optical Transmission Rate	1.0 Gb/S	2.0 Gb/S
Loss Budget	15 dB max	
Optical Return Loss	> 15 dB	
Laser Safety Classification	Class I safety per FDA/CDRH and IEC-825-1 regulations	
Typical Trans. Distances MM	500 M - 50/125μ and 300 M - 62.5/125μ	250 M - 50/125μ and 150 M - 62.5/125μ
Typical Trans. Distances SM	10 KM with 9/125 micron fiber	
Fiber Optic Connectors	ST standard, FC optional	
Signal Connectors	DB25 on input and output	
Power Requirements	9 VDC (Optional 9 - 24 VDC, 500mA)	
Power Supply Included	95 - 260 VAC, 50 - 60 Hz, 16 VA Max - Output 9VDC/.67A with Universal, US, UK, Continental Europe and Australian plugs included	
LED Annunciators Provided	Input Overload (transmitter), Optical Signal - ON (receiver)	
Operating Temperature	0 - 40 C	
Tx and Rx Dimensions	175 L x 105 W x 40 H	
Weight (each)	0.46 Kg	
Standard Warranty	Two Years, Components and Workmanship, 30 day Satisfaction Guarantee	
Accessories Supplied	DB25 Connectors for Figital Inputs/Outputs and Power Supply With International Mains	

TTI reserves the right to change specifications without notice.

To Order:

LTX-552X-X-X

Optical Transmission Rate:

0 = 1 gigabit
5 = 2 gigabit

Laser Wavelength:

850 = 850nm Multimode
1310 = 1310nm Singlemode

Optical Connector

Blank = ST
FC = FC



Made In the USA

TTI makes every effort to insure all statements and information for the products referred to in this document are accurate and reliable. TTI can not accept any responsibility for errors, omissions or miss statements, nor can they accept responsibility for any actions taken based on the information demonstrated herein. TTI reserves the right to make changes of any kind to the product referred to in this document without prior notice.

© 1/20 Terahertz Technologies Inc.